

Cordex Controller Software Upgrade

<u>Summary</u>

This procedure describes the process of upgrading the CXC controller software.

Tools/Information Required

- CXC Manual
- CXC Software CXC_Ver_X.ezip

Note: If power system is equipped with a LVD control (inhibit) switch, please throw it to Override or Inhibit position.

Software Upgrade

Download from http://www.argus.ca/downloads/

- 1. Download CXC_Ver_X.ezip software and CXC_Bootloader_v1.02.bflt to your hard-drive.
- 2. If needed, copy the Software to a floppy or CD.

Upgrade procedures using the Web Browser:

- 1. Connect you computer and CXC Controller by way of the Internet, Intranet, Ethernet direct connection (cross-over cable), Craft Port (null modem)
- 2. Select **Controller** within the screen



3. Select Upgrade Software

2 Lontroller - Microsoft Internet Explore:	<u>- U ×</u>
Ele Edit View Favorites Iools Help	1
j 4= Back • → • ② ② ঐ ঐ ② Search ≧ Eavorites ③Media ③ ▷ • 글 ③ ○ • 글 ﷺ	
Address 🙆 http://10.10.201/home.htm	▼ @G0
Links 🕘 Proman Main 🕘 Argus Main 🕌 OldProman 🔬 OldMain 🕘 Argus Intranet 🍘 Webmail 🔮 CXC 🔮 EngTimes 🔮 WebCam	
Google 🕞 🗸 💽 Go 🖗 🔊 🚱 M 🖉 🗸 😭 Bookmarks 🖌 🖓 Popups okay 👹 Check 🗸 🔌	🔘 Settings 🕶
CXC Supervisory, Burnaby, B.C. Cordex CXC v1.9174	ARGUS'
Language Logout	
Battery Vol	tage 54.21V
Normal Alarm Cut Off Submit Changes Niscard Changes Load Cut	rrent 5.3A
System Controller Rectifiers Batteries Alarms Signals Controlls Communications Hardware Logs & Files View Live Status Factory Information Date & Time Temperature Units <u>Upgrade Software</u> Upgrade Bootloader	Supervisor Reset
Controller > Upgrade Software	<u>*</u>
Controller Software Upgrade	
File Path Browse	
Submit	
	Ŧ
👔 Done 🖉 🖉 Interr	net //

4. Click Browse



5. Find the location of the files copied either on your computer, CD or floppy and choose CXC_Ver_X.ezip
Choose file



6. Press Submit



7. The screen will change and the CXC will reboot after you have pressed Accept

Controller - Microsoft Internet Explorer		
File Edit View Favorites Tools Help		1
🗢 Back 🔹 🤿 🖉 🖉 🖓 🔞 Search 👔 Favorites 🛞 Media 🧭 🔂 = 🎒 🔯 = 🗐 📖		
Address a http://10.10.10.201/home.htm		· @ 50
Links 🍯 Proman Main 🕘 Argus Main 🕌 OldProman 👜 OldMain 🍘 Argus Intranet 🍯 Webmail 🌒 CXC 🍓	EngTimes 🍪 WebCam	
🛛 Google 💽 👻 🔄 😨 😒 📉 🛃 👻 Bookmarks 🖛 🖵 Popups	; okay 🏻 🍄 Check 👻 🤇)Settings 🕶
CXC Supervisory, Burnalty, B.C.	Corder CXC v1.91T4	ARGUS'
Language Logout	/ _	
	Battery Voltage	54.20V
Normal Alarm Cut Off Submit Changes Discard Changes	Load Current	5.3A
The unit must be rebooted for the new application to take effect. Do you was	nt to reboot it now?	*
		-

- 8. During the reboot you should close your browser, allow the CXC to reboot and then regain communications with it.
- 9. Select **Controller** within the screen to verify version that you have installed.

Controller - Microsoft Internet Explorer	
Elle Edit View Favorites Tools Help	18
💠 Back 🔹 🔿 🚽 🙆 🚮 🖓 Search 💽 Favorites 🍕	Meda 🧭 🖳 - 🍠 💽 - 🗏 📖
Address () http://10.10.10.201/home.htm	▼ 6°00
nks 🕘 Proman Main 🖉 Argus Main 🔛 OldProman 💩 OldMa	ain 🕘 Argus Intranet 👩 Webmail 🍯 CXC 🍓 EngTimes 🍯 WebCam
记 🕞 🐨 🔁 🕄 🕄	💡 🍚 🎦 👻 😫 Bookmarks 🛛 📮 Popups okay 🛛 💖 Check 👻 🛛 🕥 Settings 🕶
CXC Supervisor , Burnaby, B.C.	Cordex CXC v1.02 ARGUS
Language Logout	
	Battery Voltage 54.21V
Normal Alarm Cut Off Submit Cha	nges Discard Changes Load Current 53A
	Loss ouron: even
View Live Status Factory Information Date & Ti Controller > View Live	ime Temperature Units Upgrade Software Upgrade Bootloader Reset
Controller	
Version	CXC 1.92
Date & Time	2007/7/20 8:11:40
Tech Support Number	1-888-GO-ARGUS

You have now successfully upgraded the CXC controller and thank you for choosing Argus Technologies