



## Cordex Controller Front Craft Port

### Summary


This is a general procedure on how to connect a CXC Controller to a computer via a three-wire null modem cable.


### Tools/ Reference Documents Required

- Three Wire Null Modem cable (Pin connections: 2 to 3, 3 to 2, 5 to 5, and shield ground connected on one side)
- Computer with an DB9 Communication Port (Com 1...x)
- Cordex Controller Manuals
- Hand Tools

### Part 1 – Controller Setup

1. Log in and navigate to the Communications > Craft Port
2. Select 57600 from under Baud Rate
3. Select the ✓ from bottom corner
4. Select Web Setting and set to Front Craft Port and then click ✓.





## Part 2 - Laptop Setup


### Recommended Method

The recommended method of connection for Ethernet or Craft Port is via the **CXC Connection Wizard**, it will save and restore you LAN/Com Port when you are finished using the Wizard.

The Wizard is downloadable from our website [www.Argus.ca](http://www.Argus.ca) > Support > Secure Software Downloads > Software. You will need your user name and password to download this file, if you do not have one please call our technical support line 888-462-7487, we will set it up for you.

### Alternative Method

1. Launch the Control Panel and select Network Connections for XP or Network and Dialup Connections for 2000. The following may differ slightly depending on the operating system of your laptop.
2. Launch the New Connection Wizard, the following will be examples of XP and 2000 each screen may vary.
3. Follow the screen shots and enter them as illustrated:



XP



2000




Choose your COMx




Give it a name that is meaningful to the site





### Choose your COMx



### Give it a name that is meaningful to the site




### Select Properties




### Select Configuration

Press **Finish** this will now launches the Dialup Connection

XP




Select **Properties**




Select **Configuration**


2000




Press **OK** and then **Networking** tab




Remove all checks other and TCP/IP (if possible)  
Highlight TCP/IP and then press **Properties**



Press **OK** and then **Networking** tab



Remove all checks other and TCP/IP (if possible)  
Highlight TCP/IP and then press **Properties**




Configure as illustrated and press **OK** and then **OK**

XP

2000



Configure as illustrated and press **OK** and then **OK**



Type any username and enter "1234" for the supervisory access password and "**Connect.**"

To access the Cordex web user interface launch Internet Explorer (Ver.6 or greater) and enter in the address **10.10.10.203**

**Thank you for choosing Argus Technologies**